

Z custom Zpre2

Zpre2 - Two channel preamp, 4 Audio & Video inputs with 2-way RS-232 control



Features

- Two-way RS-232 serial port connection
- Four line-level audio and four composite video inputs
- Input 1 auto select priority function, defeatable
- External IR repeater Input jack
- Remote control includes discrete codes for Off and On
- Switchable auto or manual turn on/off
- 12V trigger automatic turn/off, defeats Power button
- 12V output to trigger other components
- Record outputs for video and fixed level audio
- Headphone jack, automatically mutes line out
- Gold-plated RCA jacks
- Analog motor-driven volume control
- Outstanding design, parts quality and specs
- Voltage switchable between 115v and 230v
- Unique half-rack width chassis; 1 rack space high
- Fastening hardware available for rack mounting
- Parasound 10 year parts, 5 years labor warranty
(For USA and Canada purchases only)

Specifications

- Frequency Response – Audio
 - 10 Hz - 100 kHz, +0/-3 dB
 - 10 Hz - 50 kHz, +0/-0.8 dB
- Frequency Bandwidth – Composite Video: 10 MHz
- Total Harmonic Distortion: 0.006%
- S/N Ratio: 112 dB, input shorted, IHF A-weighted
 - 92 dB, input shorted, unweighted
- Input Impedance: 15k Ω
- Input Sensitivity: 150 mV for 1 V output
- Maximum Output: 7.6 V
- Crosstalk: 83 dB at 1 kHz; 76 dB at 20 kHz
- Tone Controls: Bass +/- 8 dB at 100 Hz
- Treble +/- 10 dB at 10 kHz
- AC Power Requirement: 110 – 120 V / 220 -240 V, 50 – 60 Hz
 - 2 watt standby; 20 watts when turned on
- Dimensions: 9 1/2" Wide x 10" Deep with connectors x 2" High with feet
 - 13.4" panel only, 241 x 254 x 50mm, 44.1mm panel only
- Net Weight: 4.6 lbs, 2.1 kg



PARASOUND

Parasound Products, Inc. 950 Battery Street, San Francisco, CA 94111
415-397-7100 / FAX 415-397-0144 www.parasound.com